

Main (7.1) Output				
Function	Channel	Function	Pin	Connector Rear
		Chassis	13	
		Gnd	25	
Left	1	Cold	12	
		Hot	24	
		Gnd	11	
Right	2	Cold	23	
		Hot	10	
		Gnd	22	
Center	3	Cold	9	
		Hot	21	
		Gnd	8	
LFE	4	Cold	20	
		Hot	7	
		Gnd	19	
L.Side	5	Cold	6	
		Hot	18	
		Gnd	5	
R.Side	6	Cold	17	
		Hot	4	
		Gnd	16	
L.Back	7	Cold	3	
		Hot	15	
		Gnd	2	
R.back	8	Cold	14	
		Hot	1	

Alt(5.1) & Mini (Stereo) Output				
Function	Channel	Function	Pin	Connector Rear
		Chassis	13	
		Chassis	13	
5.1 Left	1	Gnd	25	
		Cold	12	
		Hot	24	
5.1 Right	2	Gnd	11	
		Cold	23	
		Hot	10	
5.1 Center	3	Gnd	22	
		Cold	9	
		Hot	21	
5.1 LFE	4	Gnd	8	
		Cold	20	
		Hot	7	
5.1 L.Side	5	Gnd	19	
		Cold	6	
		Hot	18	
5.1 R.Side	6	Gnd	5	
		Cold	17	
		Hot	4	
Mini Left	7	Gnd	16	
		Cold	3	
		Hot	15	
Mini Right	8	Gnd	2	
		Cold	14	
		Hot	1	

Main (7.1) Input				Connector Rear
Function	Channel	Function	Pin	
		Chassis	13	
Left	1	Gnd	25	
		Cold	12	
		Hot	24	
Right	2	Gnd	11	
		Cold	23	
		Hot	10	
Center	3	Gnd	22	
		Cold	9	
		Hot	21	
LFE	4	Gnd	8	
		Cold	20	
		Hot	7	
L.Side	5	Gnd	19	
		Cold	6	
		Hot	18	
R.Side	6	Gnd	5	
		Cold	17	
		Hot	4	
L.Back	7	Gnd	16	
		Cold	3	
		Hot	15	
R.back	8	Gnd	2	
		Cold	14	
		Hot	1	

Alt(5.1) & Cue 3 Input				Connector Rear
Function	Channel	Function	Pin	
		Chassis	13	
5.1 Left	1	Gnd	25	
		Cold	12	
		Hot	24	
5.1 Right	2	Gnd	11	
		Cold	23	
		Hot	10	
5.1 Center	3	Gnd	22	
		Cold	9	
		Hot	21	
5.1 LFE	4	Gnd	8	
		Cold	20	
		Hot	7	
5.1 L.Side	5	Gnd	19	
		Cold	6	
		Hot	18	
5.1 R.Side	6	Gnd	5	
		Cold	17	
		Hot	4	
Cue 3 Left	7	Gnd	16	
		Cold	3	
		Hot	15	
Cue 3 Right	8	Gnd	2	
		Cold	14	
		Hot	1	

Stereo Inputs				
Function	Channel	Function	Pin	Connector Rear
		Chassis	13	
		Gnd	25	
Stereo 1 Left	1	Cold	12	
		Hot	24	
		Gnd	11	
Stereo 1 Right	2	Cold	23	
		Hot	10	
		Gnd	22	
Stereo 2 Left	3	Cold	9	
		Hot	21	
		Gnd	8	
Stereo 2 Right	4	Cold	20	
		Hot	7	
		Gnd	19	
Stereo 3 Left	5	Cold	6	
		Hot	18	
		Gnd	5	
Stereo 3 Right	6	Cold	17	
		Hot	4	
		Gnd	16	
Stereo 4 Left	7	Cold	3	
		Hot	15	
		Gnd	2	
Stereo 4 Right	8	Cold	14	
		Hot	1	

T/B, L/B, Cue 1 & 2 Input				
Function	Channel	Function	Pin	Connector Rear
		Chassis	13	
		Gnd	25	
Internal T/B	1	Cold	12	
		Hot	24	
		Gnd	11	
External T/B	2	Cold	23	
		Hot	10	
		Gnd	22	
Listen 1	3	Cold	9	
		Hot	21	
		Gnd	8	
Listen 2	4	Cold	20	
		Hot	7	
		Gnd	19	
Cue 1 Left	5	Cold	6	
		Hot	18	
		Gnd	5	
Cue 1 Right	6	Cold	17	
		Hot	4	
		Gnd	16	
Cue 2 Left	7	Cold	3	
		Hot	15	
		Gnd	2	
Cue 2 Right	8	Cold	14	
		Hot	1	

Xpand Inputs – 7.1.4				
Function	Channel	Function	Pin	Connector Rear
		Chassis	13	
		Gnd	25	
Left Top Front	1	Cold	12	
		Hot	24	
		Gnd	11	
Right Top Front	2	Cold	23	
		Hot	10	
		Gnd	22	
Left Top Back	3	Cold	9	
		Hot	21	
		Gnd	8	
Right Top Back	4	Cold	20	
		Hot	7	
		Gnd	19	
Left Side	5	Cold	6	
		Hot	18	
		Gnd	5	
Right Side	6	Cold	17	
		Hot	4	
		Gnd	16	
Left Back	7	Cold	3	
		Hot	15	
		Gnd	2	
Right Back	8	Cold	14	
		Hot	1	

Xpand Outputs – 7.1.4				
Function	Channel	Function	Pin	Connector Rear
		Chassis	13	
		Gnd	25	
Left Top Front	1	Cold	12	
		Hot	24	
		Gnd	11	
Right Top Front	2	Cold	23	
		Hot	10	
		Gnd	22	
Left Top Back	3	Cold	9	
		Hot	21	
		Gnd	8	
Right Top Back	4	Cold	20	
		Hot	7	
		Gnd	19	
Left Back BassX	5	Cold	6	
		Hot	18	
		Gnd	5	
Right Back BassX	6	Cold	17	
		Hot	4	
		Gnd	16	
Left Back	7	Cold	3	
		Hot	15	
		Gnd	2	
Right Back	8	Cold	14	
		Hot	1	