




MAC Mini-Din Pinout

Macintosh Mini-DIN-8 plug

- male viewed from front - pins side
- flip horizontal for female socket - pins



Pins

1. KSKo : output handshake - DTR
2. HSKi/External clock : input handshake - CTS
3. TxD- : Transmit data line negative - use for RS232
4. Ground
5. RxD- : Receive data line negative - use for RS232
6. TxD+ : Transmit data line positive - open for RS232
7. not connected : DCD
8. RxD+ : Receive data line positive - ground for RS232

Sony 9 Pin Machine Control Converter		
Mini Din		9 Pin 'D'
Pin	Function	Pin
	Chassis	1
5	Rx -	2
6	Tx +	3
4	Ground	4
		5
		6
8	Rx +	7
3	Tx-	8
		9

Sony 9 Pin Machine Emulation Converter		
Mini Din		9 Pin 'D'
Pin	Function	Pin
	Chassis	1
3	Tx -	2
8	Rx +	3
4	Ground	4
		5
		6
6	Tx +	7
5	Rx-	8
		9

CB Electronics

Loddonside, Lands End House, Beggars Hill Road, Charvil, Berkshire, RG10 0UD, UK
 Tel +44 (0) 1189 320345 Fax +44 (0) 1189 320346
<http://www.colinbroad.com> E-mail Support@colinbroad.com